

Cordless Cap Lamp

Performance series – for Underground Hardrock Mines, Tunnels and Petrochemical Environments

Features



Three operating modes – Main, High Beam, Auxiliary



Adjustable beam angle to point wherever you look



Lightweight, comfortable and ergonomic



Rugged casing made from GERMAN FRAS material for rough handling & wide ambient temperature range



World's safest and most reliable Panasonic battery



Made from Top Brand, high quality components and parts



UHF 860 - 960 MHz RFID can be integrated into registration and access control systems



13.56 MHz for use with your Kiosk, Digital Tagboard and Inventory solutions



Product Specifications



IP Rating - IP67

Submersible in water up to 1m for 30min



Illumination

7000 Lx Main Mode
10000 Lx High-Beam Mode



Charging Time

9 h



Running Time

14 h Main Mode



Ambient Temperature

-20°C ≤ Ta ≤ 40°C



Weight

154 g

Certifications:

- Certificate #: IECEx TSA 19.0008
- Ex Marking: Ex ia op is IIA T3 Ga

Standard #:

- IEC 60079-0
- IEC 60079-11
- IEC 60079-28



Roobuck Pty Limited
Suite 6, 20 West Street
Brookvale, NSW 2100
Australia



+61 2 9938 1550



info@roobuck.com.au



roobuck.com.au
roobuck.com
roobuck.co

CB8E Charging Bank For 8 Cordless Cap Lamps



Features

- Portable, Wall Mountable, Vehicle Installation
- Locking Plate is optional extra (CB8(E)-LPU)
- Charging Connection Indicator
- Automatic over-load protection – cuts off that circuit when Cap Lamp battery is fully charged

Specifications

Input	240 VAC or 12-24 VDC
Dimensions	33 x 21 x 5.5 cm
Weight	1.1 kg

CB35E/CB53E - Charging Banks For 35/53 Cordless Cap Lamps

Features

- Automatic over-load protection – cuts off the circuit when Cap Lamp battery is fully charged
- Label groove
- Padlock bracket
- Charging Connection Indicator
- Includes wall mounting kit
- 2 x foot pads for CB53E
- Circuits are easily accessible for servicing

Specifications

Input	240 VAC	
Dimensions	CB35E: 87 x 11 x 56 cm	CB53E: 84 x 13 x 110 cm
Weight	CB35E: 17 kg	CB53E: 31 kg



Individual Chargers & Accessories

MCE: Single Mains Charger - AU, EU, UK, USA
UCE: Single USB Charger



Roobuck Pty Limited
Suite 6, 20 West Street
Brookvale, NSW 2100
Australia



+61 2 9938 1550



info@roobuck.com.au



roobuck.com.au
roobuck.com
roobuck.co